

TRUTEST801 Smoke detector sensitivity tester

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Compatible with analog-addressable, addressable, or conventional ionization and photoelectric detectors
- ▶ Automatic self-calibration before each test
- ▶ Telescopic adjustment to over 20 ft (6 m) with the optional SOLO100 Telescopic Access Pole
- ▶ Lightweight and portable
- ▶ Easy to use

The TRUTEST801 introduces a measured amount of smoke aerosol (SMOKE400, not supplied) into the installed smoke detector's smoke chamber. It operates using a precision closed-loop system that measures the smoke obscuration and feeds information back to a controlling microprocessor. It then displays the sensitivity reading in %/ft. on a liquid crystal display (LCD) screen.

Certifications and approvals

No Climb Products Ltd. holds these Listings and Approvals:

Region	Regulatory compliance/quality marks	
USA	UL	UL 268, Smoke Detectors for Fire Alarm Systems

Installation/configuration notes

The TRUTEST801 requires either the SOLO100 Telescopic pole (1-3.38 m) or the SOLO101 Extension pole (1 m). Neither is supplied.

Parts included

Quantity	Component
1	Main unit
1	Control unit
2	Interconnecting cables (different lengths)
1	Height adjustment clamp
2	Membrane seals (different apertures)
1	Battery charger
1	Carry case
1	Literature pack

Technical specifications

Environmental

Relative Humidity:	up to 85%, non-condensing
Temperature (operating):	+50°F to +95°F (+10°C to +35°C)
Temperature (storage):	+15°F to +120°F (-10°C to +50°C)

Mechanical

Dimensions (LxWxH)	0.870 m x 0.381 m x 0.254 m (34.25 in. x 15 in. x 10 in.)
Weight	
gross	11.250 kg (24.8 lb.)
net	9.885 kg (21.8 lb.)

Trademarks

All hardware and software product names used in this document are likely to be registered trademarks and must be treated accordingly.

Ordering information

TRUTEST801 Smoke detector sensitivity tester

Uses a precision closed-loop system to measure smoke obscuration. Then displays the sensitivity reading in %/ft. on a liquid crystal display (LCD) screen

Order number **TRUTEST801**

Accessories

SOLO100 Telescopic access pole

Enables the installation and replacement of fire detectors at high ceilings. Expandable with up to three SOLO101 Fixed extension poles. In the Americas, the product is labelled SOLO100. Elsewhere, the product is labelled SOLO106-126.

Order number **SOLO100**

SOLO101 Extension pole

Enables the installation and replacement of fire detectors on ceilings. Expandable with other fixed extension poles. Can be used to extend the SOLO100 Telescopic access pole.

Order number **SOLO101**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia